



### EASi DRIVER 36W

16.5  
60  
202  
218

### EASi DRIVER 72W

16.5  
70  
286  
306

### EASi DRIVER 36/12R

IN 12V OUT

Micro 12

220-240 VAC

PRI: 220-240Vac, 50/60Hz, 0.20A, cos (φ) 0.95  
SEC: 12Vdc, 0-3A, 36W max.  
ta: -20...+40°C tc: max. 90 °C

### EASi DRIVER 36/2 4D

IN 24V OUT

Micro 24

220-240 VAC

PRI: 220-240Vac, 50/60Hz, 0.20A, cos (φ) 0.95  
SEC: 24Vdc, 0-1.5A, 36W max.  
ta: -20...+40°C tc: max. 85 °C

### EASi DRIVER 7 2/12R

IN 12V OUT

Micro 12

max. 36W  
12Vdc 12Vdc

220-240 VAC

PRI: 220-240Vac, 50/60Hz, 0.35A, cos (φ) 0.95  
SEC: 12Vdc, 0-6A, 72W max.  
ta: -20...+40°C tc: max. 90 °C

### EASi DRIVER 7 2/24D

IN 24V OUT

Micro 24

220-240 VAC

PRI: 220-240Vac, 50/60Hz, 0.35A, cos (φ) 0.95  
SEC: 24Vdc, 0-3A, 72W max.  
ta: -20...+40°C tc: max. 90 °C

